

16 Slot Rack Mountable

100BASE-10GBASE MCC

Media Converter Chassis, Media Converter Cards



Features

Interface/Ports:	1 x RJ-45, 1 X SC, ST, SFP, SFP+, XFP
Connectivity:	Twisted Pair, Fiber
Connectivity Media:	10/100Base-TX Twisted Pair 100Base-FX (50/125 μm , 62.5/125 μm MMF) (9/125 μm SMF) 1000Base-XX, 10GBase
Distance Supported:	550m, 2km, 20km
Wavelength:	1310nm, 1550nm
Network Technology:	10/100Base-TX, 100Base-FX, 1000Base-XX
Status Indicators:	Power Copper Link Fiber Link Copper Receive activity Fiber Receive activity
Input Voltage:	120V
Input Current:	Chassis: 16A, Card: 750mA
Temperature:	32°F (0°C) ~ 122°F (50°C)
Humidity:	5 ~ 90% Non-condensing

Product Description

The 16 Slot Racks are 19" rack mountable 10/100/1000M fiber media converter. Offering a great space/performance ratio, the 16 Slot Racks covers various fiber media converter functions including variety of data rate, SM/MM, single fiber and double fiber with simple setup. The ADD-MRACK-16 and ADD-MRACK-16 are standard with Dual redundant power supply.

AddOn Media Network Interface Cards are 100% compliant for all of your networking needs. Media Converter Cards provides a 10/100/1000M Base-TX to 1000Base-XX MMF and SMF fiber port. Economically priced.

ADD-RACK-16

Media Converter Chassis 19"
16-Slot Dual-Power Rack Mount

ADD-MRACK-16

Managed Media Converter Chassis 19"
16-Slot Dual-Power Rack Mount

ADD-MCC1MMM2K

Media Converter Card 100FX
10/100M 1310NM MMF SC 2km Reach

ADD-MCC1MSM20

Media Converter Card 100LX
10/100M 1310NM SMF 20km Reach

ADD-MCC1MBX53

Media Converter Card 100BXD
1550/1310NM SMF SC BiDi 20km Reach

ADD-MCC1GMM5M

Media Converter Card 1000BSX
10/100/1000M 850NM MMF SC 550m

ADD-MCC1GSM20

Media Converter Card 1000BLX
10/100/1000M 1310NM SMF SC 20km

ADD-MCCTXSFP*

Media Converter Card 1000BT-SPF
10/100/1000M with Open SFP Slot

ADD-MCC10G2SFP*

Media Converter Card 10G
OEO Converter 2 Open SFP+ Slots

ADD-MCC10GX SFP*

Media Converter Card 10G
OEO Converter SFP+ and XFP Slot

ADD-MCC10G2XFP*

Media Converter Card 10G
OEO Converter 2 Open XFP Slots

ADD-MCC4G2SFP*

Media Converter Card 125M to 4G
OEO Converter 2 Open SFP Slots